


# X-EM 6H, X-EW 6H, X-EF 7H, X-EM 8H, X-EM 10H, X-EW 10H Threaded Studs for Steel

#### **Product data**


M6/W61

#### **Dimensions**

X-EM6H/EW6H- -9 FP8 X-EF7H-7-9 FP8 |ø3.7









IM8

X-EM8H-15-12 FP10



X-EM10H-24-12 P10





For dimension details see chapter fastener selection

#### **General information**

#### Material specifications

Carbon steel shank: HRC 56.5 Zinc coating: 1) 5-13 µm

1) Zinc coating (electroplating for corrosion protection during construction and service in protected environment)

## Fastening tools

DX 460, DX 76, DX 76 PTR, DX 600 N

See fastener selection for more details.


#### Approvals

ICC-ES ESR-2347	X-EW6H, X-EW10H,
(USA):	X-EM8H
FM 3026695:	X-EW6H, X-EW10H
UL: EX2258:	X-EW6H, X-EW10H
ABS LR:	all types




## **Applications**


#### Examples




Base plates for pipe rings



Hanging with threaded couplers



**Electrical boxes** 



Miscellaneous attachments



## Load data


#### Recommended loads

Fastener designation	Shank <b>d</b> <sub>s</sub> x <b>L</b> <sub>s</sub> [mm]	N <sub>rec</sub> [kN]	V <sub>rec</sub> [kN]	M <sub>rec</sub> [Nm]
X-EM6H, X-EW6H, X-EF7H	3.7 x 8.5	1.6	1.6	5.0
X-EM8H, X-EM10H	4.5 x 12.0	2.4	2.4	9.0
X-EW10H-30-14	5.2 x 15.0	3.0	3.0	14.0

#### Conditions

- Redundancy (multiple fastening) must be provided.
- Global factor of safety for static pull-out >3 (based on 5% fractile value).
- Predominantly static loading.
- Strength of fastened material must be considered.
- Observance of all application limitations and recommendations.
- The recommended loads in the table refer to the resistance of the individual fastening and may not be the same as the loads F<sub>N</sub> and F<sub>V</sub> acting on the fastened part.
  Note: If relevant, prying forces need to be considered in design, see example.
  Moment acting on fastener shank only in case of a gap between base and fastened material.





2.114




## **Application requirements**

## Thickness of base material

Minimum steel thickness:

	t <sub>II</sub>
X-EM6H/EW6H, X-EF7H	≥ 4 mm
X-EM8H/EW8H, X-EM10H/EW10H	≥ 6 mm




## Thickness of fastened material


$$t_l \le L_g - t_{washer} - t_{nut} \cong 1.5-33.0 \text{ mm}$$



## Spacing and edge distances

Edge distance and spacing: c = s ≥ 15 mm





## **Corrosion information**


The intended use only comprises fastenings which are not directly exposed to external weather conditions or moist atmospheres. For further detailed information on corrosion see relevant chapter in **Direct Fastening Principles and Technique** section.

8/2011 2.115



## **Application limits**

## X-EM6H, X-EW6H, X-EF7H




DX 460 tool:

① X-EF7H- -9

2 X-EM6H-\_\_9,

X-EW6H-\_\_-9

#### X-EM8H



DX 460 tool:


① X-EM8H- -12

DX 76 / DX 76 PTR tool

with X-76-F10-PTR fastener guide:

2 X-EM8H-15-12

#### X-EM10H / EW10H



DX 76 / DX 76 PTR tool:

① X-EM10H-24-12

DX 600 N tool:

2 X-EW10H-30-14 P10

2.116 8/2011



#### Fastener selection and system recommendation Base material Fastened Threading Shank DX tools Fastener thickness thickness Item no. length lengths Designation<sup>1</sup>) La [mm] L<sub>s</sub> [mm] t<sub>II.min</sub> [mm] t<sub>l.max</sub> [mm] 4.0 1.5 X-EM6H-8-9 FP8 271965 8 8.5 DX 460 4.5 DX 460 X-EM6H-11-9 FP8 271963 11 8.5 13.5 X-EM6H-20-9 FP8 20 8.5 DX 460 271961 4.5 X-EW6H-11-9 FP8 271973 11 8.5 DX 460 13.5 X-EW6H-20-9 FP8 271971 20 8.5 DX 460 21.5 X-EW6H-28-9 FP8 271969 28 8.5 DX 460 31.5 X-EW6H-38-9 FP8 38 8.5 DX 460 271967 7 0.5 X-EF7H-7-9 FS8 271975 10 DX 460 6.0 2.0 X-EM8H-11-12 P8 11 12 DX 460 271983 6.0 X-EM8H-15-12 P8 271981 15 12 DX 460 6.0 X-EM8H-15-12 FP10 271982 15 12 DX 76 PTR, DX 460 14.0 X-EM10H-24-12 P10 271984 24 12 DX 76 PTR, DX 460 20.0 **X-EW10H-30-14 P10** 271985 30 14 DX 600 N

#### **Cartridge recommendation**

Tool energy adjustment by installation tests on site

Fastener	Cartridge selection	DX tool
X-EM6H, X-EW6H, X-EF7H	6.8/11M green or yellow cartridges	DX 460
X-EM8H	6.8/18M blue cartridges	DX 76,
		DX 76 PTR
	6.8/11M yellow, red or black cartridges	DX 460
X-EM10H	6.8/18M blue, red or black cartridges	DX 76,
		DX 76 PTR
	6.8/11M yellow, red or black cartridges	DX 460
X-EW10H	6.8/18 red or black cartridges	DX 600N

8/2011 2.117


<sup>1)</sup> Type of threading:  $\mathbf{M} = \text{metric}$ ;  $\mathbf{W6}$ ,  $\mathbf{W10} = \text{Whitworth} \frac{1}{4}$ ;  $\frac{3}{8}$ ;  $\mathbf{F7} = \text{French 7 mm}$ 




# Fastening quality assurance


## **Fastening inspection**


# X-EM6H, X-EW6H, X-EF7H





X-EM8H, X-EM10H, X-EW10H





Nail standoff **Tightening torque** 


Fastener	h <sub>NVS</sub> [mm]	T <sub>rec</sub> [Nm]
X-EM6H-8-9	8.0–11.0	≤ 4
X-EM6H-/X-EW6H-11-9	9.5–12.5	≤ 4
X-EM6H-/X-EW6H-20-9	18.5–21.5	≤ 4
X-EW6H-28-9	26.5–29.5	≤ 4
X-EW6H-38-9	36.5–39.5	≤ 4
X-EF7H-7-9	9.0–12.0	≤ 4

Nail standoff **Tightening torque** 

Fastener	[mm]	l rec [Nm]
X-EM8H-11-12	11.5–15.5	≤10.5
X-EM8H-15-12	15.5–19.5	≤10.5
X-EM10H-24-12	26.5–30.5	≤10.5
X-EW10H-30-14	28.0-31.0	≤15.0

## Installation

Arrangement to prevent moment on shank: Coupler tight against steel



2.118 8/2011